会TDK

Testing GBDriver RS4 Data Randomizer Effectiveness

RELATED PRODUCTS	GBDRIVER RS4 (SATA SSD Controller) SDG4A Series (2.5" SATA 3Gbps SSD) SHG4A Series (SATA 3Gbps Half Slim SSD)											
TESTED DATE	2013/9/4 10:20 ~ 2013/9/27 11:30											
TESTED BY	TDK Corp, Flash Memory Applied Business, ESS BU [H. Kamata]											
TEST PROCEDURE	(1) Executed 1,000 times Read to the following flash memory chips, logged bit error. No.1: Program/Erase (P/E) Cycle 0 No.2: P/E Cycle 1											
	No.3: P/E Cycle						1000	-				
	No.4: P/E Cycle						2000	-				
	No.5: P/E Cycle						3000	-				
	(2) Executed 10 million times Read to No.5 chip, logged bit error.											
SAMPLES	(WEEKLY process:					i-level cell 1xn 6KB/Page		(WEEKLY CODE: 1320L3901)				
] PCS [NAND:						- i `	CONTROLLER:				
	(WEEKLY CODE:						(WEEKLY CODE:)					
RESULTS	RANDOMIZER ON							RANDOMIZER OFF				
P/E	<u>1</u>	<u>500</u>	<u>1,000</u>	<u>2,000</u>	<u>5,000</u>	<u>10,000</u>	<u>1</u>	<u>500</u>	<u>1,000</u>	<u>2,000</u>	<u>5,000</u>	<u>10,000</u>
0	0						0					
1 1000	3						3	•••				
2000	15						20					
3000	28	29	29	33	43	44	43	44	44	44	44	44

