HWS150A/MEA

SPECIFICATIONS

A259-01-01/MEA

MODEL				HWS150A	HWS150A	HWS150A	HWS150A	HWS150A	
MODEL									
ITEMS				-5/MEA	-12/MEA	-15/MEA	-24/MEA	-48/MEA	
1	Nominal Output Voltage		V	5	12	15	24	48	
2	Maximum Output Current		Α	30	13	10	6.5	3.3	
3	Maximum Output Power		W	150.0	156.0	150.0	156.0	158.4	
4	Efficiency (Typ.) (*1) 100V	_	%	85	85	86	88	89	
	200V		%	87	88	89	90	91	
5	Input Voltage Range (*2)		-	85 - 265VAC (47 - 63Hz) or 120 - 370VDC					
6		(*1)	A	1.9/0.95					
7	Inrush Current (Typ.) (*1)	(*4)	-	14A at 100VAC, 28A at 200VAC, Ta=25°C, Cold Start					
8	PFHC		-	Designed to meet IEC61000-3-2					
9	Voltage Fluctuations / Flicker Emissions -			Designed to meet IEC61000-3-3					
10	Power Factor (Typ.) (*1)			0.98/0.93					
11	Output Voltage Range		V	4.0 - 6.0	9.6 - 14.4	12.0 - 18.0	19.2 - 28.8	38.4 - 52.8	
12	Maximum Ripple & Noise 0 <tas< td=""><td>70°C</td><td>mV</td><td>120</td><td>150</td><td>150</td><td>150</td><td>200</td></tas<>	70°C	mV	120	150	150	150	200	
	(*5) -10≤Ta	<0°C	mV	160	180	180	180	240	
13	Maximum Line Regulation	(*6)	mV	20	48	60	96	192	
14	Maximum Load Regulation	(*7)	mV	40	96	120	150	240	
15	Temperature Coefficient		-	Less than 0.02% / °C					
16		(*8)	Α	31.5 <u>≤</u>	13.6 ≤	10.5 ≤	6.82 <u>≤</u>	3.46 ≤	
17	Over Voltage Protection	(*9)	V	6.25 - 7.25	15.0 - 17.4	18.8 - 21.8	30.0 - 34.8	55.2 - 64.8	
18	Hold-up Time (Typ.)	(*1)	-	20ms					
19	Leakage Current (*	10)	-	Less than 0.5mA. 0.2mA (Typ) at 100VAC / 0.4mA (Typ) at 230VAC					
20	Remote Sensing		-	Possible					
21	Parallel Operation		-	-					
22	Series Operation		-	Possible					
23	Operating Temperature (*	11)	-	-10 to +70°C (-10 to +50°C:100%, +60°C:60%, +70°C:20%)					
24	Operating Humidity		-	30 to 90%RH (No Condensing)					
25	Storage Temperature		-	-30 to +85°C					
26	Storage Humidity		-	10 to 95%RH (No Condensing)					
27	Cooling		-	Convection Cooling					
28	Withstand Voltage - Input - FG : 2kVAC (20mA), Input - Output : 3kVAC (20mA)						20mA)		
	Output - FG : 500VAC (20mA) for 1min					,			
29	Isolation Resistance		-	More than 100MΩ at 25°C and 70%RH Output - FG: 500VDC					
30	Vibration	- At no operating, 10 - 55Hz (Sweep for 1min)							
		- 1		19.6m/s ² Constant, X,Y,Z 1hour each.					
31	Shock		-	Less than 196.1m/s ²					
32		12)	-	Approved by ES60601-1, EN60601-1, CSA-C22.2 No.60601-1					
33	Line DIP		-	Designed to meet SEMI-F47 (200VAC Line only)					
34		·13)	-	Designed to meet EN55011/EN55022-B, FCC-B, VCCI-B					
35		13)	-	Designed to meet EN55011/EN55022-B, FCC-B, VCCI-B					
		13)	-	Designed to meet IEC61000-6-2 IEC61000-4-2, -3, -4, -5, -6, -8, -11					
37	Weight (Typ) - 520g								
	Size (W x H x D) mm 42 x 82 x 160 (Refer to Outline Drawing)								
*Read instruction manual carefully, before using the nower supply unit									

*Read instruction manual carefully, before using the power supply unit.

- *1. At 100VAC/200VAC, Ta=25°C, nominal output voltage and maximum output power.
- *2. For cases where conformance to various safety specs (ES, CSA, EN) are required, to be described as 100 240VAC(50 60Hz).
- *3. Output derating needed when input voltage less than 90VAC. Refer to OUTPUT DERATING CURVE (A259-01-02/A-).
- *4. Not applicable for the inrush current to Noise Filter for less than 0.2ms.
- *5. Measure with JEITA RC-9131B probe, Bandwidth of scope :100MHz.
- *6. 85 265VAC, constant load.
- *7. No load-Full load, constant input voltage.
- *8. Constant current limit and Hiccup with automatic recovery. Avoid to operate at over load or short circuit condition.
- *9. OVP circuit will shut down output, manual reset (Re power on).
- *10. Measured by the each measuring method of ES, CSA and EN (at 60Hz).
- *11. Output Derating
 - Derating at standard mounting. Refer to OUTPUT DERATING CURVE (A259-01-02/A-_).
 - Load (%) is percent of maximum output power or maximum output current, do not exceed its derating of maximum load.
- *12. As for ES60601-1, EN60601-1 and CSA-C22.2 No.60601-1, 3rd Edition and MOOP level.
- *13. The power supply is considered a component which will be installed into a final equipment.

The final equipment should be re-evaluated that it meets EMC directives.

⁼NOTES=